



FA300

300 W FM POWER AMPLIFIER



The FA300 FM Amplifier is designed to provide more reliable FM transmitters using the extremely rugged LDMOS power transistor for the FM broadcast market.

Main Features

- Very Efficient LDMOS Amplifier
- Measurement and display of the transmitter's working parameters
- Seven Selectable Complete Set-up Ready For Use N+1 System
- Automatic start/stop for air conditioner
- Event logs can be seen on display or printed out with date&time of event
- High Reliability Use Of Microstrip Technology
- VSWR>65:1

Options

- GSM/GPRS Modem for internet connection
- Remote Control Via Internet (TCP/IP, SNMP)





FA300

300 W FM POWER AMPLIFIER

Technical Parameters		
RF DATA	Operating Frequency	87.5-108.0 MHz
	RF Power Input	10W
	RF Power Output	300W
	RF Input Connection	N
	RF Output Connection	7/16
	In / Out Impedences	50Ω
	RF Probe	-50 dBm, 50 Ohm, BNC
	Power Stability	<1%
	Overall Efficiency	75%
	Spurious and harmonic suppression (ref. to carrier)	< - 80 dBc
	Synchronous AM (ref.100% mod.)	< - 58 dB
	Asynchronous AM (ref.100% mod.)	< - 50 dB
	MEASURED VALUES	Forward Power
Relected power		
DC supply voltage of each RFstage		
DC supply current of each RFstage		
Heat sink Temperature		
Environmental Temperature		
Humidity		
ENVIRONMENTAL	Cooling	forced air by internal fans
	Service	continuous 7/24 h
	Operating temperature	15 to + 45°C/ 5 to + 104°F
	Max. Installation altitude	4000m on seal evels
POWER	AC Voltage	90/264 VAC-47- 63 Hz
	Power consumption	480VA
PHYSICAL FEATURES	Height	3U (13.5cm)
	Depth	49 cm deep including connectors
	Width	48.5 cm Rack Mountable
	Weight	16 kg